

reset SG300-10



context

dit document beschrijft hoe Cisco SG300-10 switch reset naar fabrieksinstellingen

stappenplan

- verbind de switch met je laptop ahv [console](#) kabel
- start de switch op en wacht tot je de login prompt krijgt
- druk met een paperclip de **reset**-knop in

A screenshot of a PuTTY terminal window titled "COM6 - PuTTY". The text displayed is: "User Name: To perform reset to factory defaults do not release the button for 10 seconds. Resetting local unit to Factory Defaults". Below this, there is a separator line of asterisks, followed by "SYSTEM RESET" in the center, and another separator line of asterisks. A green cursor is visible at the bottom left.

- houd de knop 10 seconden ingedrukt tot alle lichtjes branden
- nu wordt de switch reset naar **factory defaults**
 - standaard boot image
 - aanmaken RSA keys
 - standaard waarden herstellen

A screenshot of a PuTTY terminal window titled "COM6 - PuTTY". The text displayed includes: "Tapi Version: v1.9.6", "Core Version: v1.9.6", and a timestamp "06-Aug-2014 16:56:14 %INIT-I-InitCompleted: Initialization task is completed". It then shows "06-Aug-2014 16:56:27 %SNMP-I-CDBITEMSNUM: Number of running configuration items loaded: 0" and "06-Aug-2014 16:56:27 %SNMP-I-CDBITEMSNUM: Number of startup configuration items loaded: 0". This is followed by several lines about generating default RSA and DSA keys for the SSH server and client, with timestamps. It then shows "06-Aug-2014 16:57:14 %SYSLOG-N-LOGGING: Logging started." and "06-Aug-2014 16:57:45 %SSL-I-SSLCTASK: Starting autogeneration of self-signed certificate - 1024 bits". Below this, it says "Generating RSA private key, 1024 bit long modulus" and "06-Aug-2014 16:57:51 %SSL-I-SSLCTASK: Autogeneration of self-signed certificate was successfully completed". It then says "Generating RSA private key, 1024 bit long modulus" again. The last line visible is "Console baud-rate auto detection is enabled, press Enter twice to complete the detection process". At the bottom, "User Name:" is followed by a green cursor.

- meld aan met **cisco/cisco**

- voer standaard [installatie switch](#) uit.

getest op

- Cisco SG300-10

meer info

voeg hier linken toe naar verdere uitleg

[cisco](#)

From:

<https://www.louslab.be/> - **Lou's lab**

Permanent link:

https://www.louslab.be/doku.php?id=cisco:reset_sg300-10

Last update: **2026/03/14 18:39**

